

American Voyager Association

<http://www.amervoyassoc.org>

Wiring your motorcycle for trailer lights- By Bob Silvano

You can access the wires for the rear lights under the seat on the right hand side.

We recommend using a powered isolator for 5 wire trailers, or a powered isolator/converter for 4 wire trailers. If your trailer is equipped with all L.E.D. lights an isolator is not a necessity, however using an isolator will help protect your bikes electrical/computer system should you develop a direct short.

If your trailer is **NOT** equipped with L.E.D. lights you will need an isolator

Be sure to route all wires to the rear of the bike in a safe manner, using a wire loom cover etc. Avoid all sharp edges and use plastic wire ties to secure the wires in place.

www.amervoyassoc.org



Kawasaki 1700 Voyager Wire Color Code

Brake = Blue

Left Turn = Green

Right Turn = Gray

Tail Light = Red

Ground = Black / Yellow